

Optical Smoke Detector

FI750/O



- **Loop technology with Labor Strauss protocol**
- **Application-specific setting of the response behaviour**
- **Double dust trap and insect screen**
- **Up to 240 devices per loop**
- **Output for remote indicator**
- **Function check by means of test magnet or test gas**



Description

The addressable Optical Smoke Detector FI750/O uses the light scattering principle and was developed for the detection of smoke particles in a wide range of fire detection applications. A symmetrical sensing chamber allows for optimal smoke sensitivity from all directions.

In order to avoid false alarms, a fine-meshed protective grid effectively keeps dust, ambient light and insects from entering the detector. In addition, the special design of the case makes it more difficult for dust to settle inside the sensing chamber.

The influence of contamination of the optical measurement system is additionally compensated for by using intelligent evaluation algorithms. As a result, the response sensitivity of the detector is kept constant for a long time – a further effective step to avoid false alarms.

The loop technology with Labor Strauss protocol establishes a permanent communication between the fire detection control panel and the detector. That ensures periodical function testing of the detector.

Up to 240 loop elements can be addressed on a Labor Strauss loop. In this way, extensive fire detection systems can be designed with a minimum expense in cabling.

By parameterising the control panel accordingly, the response behaviour of the detector can be set to one of four levels and, as a result, the detector can be specifically adapted for the respective application.

The two multicoloured LED displays on the detector are visible from all directions, thus facilitating the identification of the activated detector. The alarm condition is indicated in red and the test condition in green. Furthermore, an output is available for the connection of an optional remote indicator. The output can be freely parameterised on a compatible fire detection control panel.

An integrated dual-isolator disconnects the loop in case of a short circuit. In this way, the undisturbed communication with the loop elements outside the faulty loop section is ensured.

The detector address is set by means of the hand-held Programming Unit FI750/PU within the range 1 to 240. In addition, the programming unit allows several parameters, such as the level of contamination of the optical chamber, the default analogue value or the production date to be read out. Alternatively, the detector can be addressed automatically if it is connected to a compatible fire detection control panel.

A detector function test can be conveniently conducted by using a test magnet or an aerosol spray.



2831-CPR-F4314

Building Safety. Building Security.

LST

Specifications

Operating voltage	Supply through loop voltage
Current consumption at 24V	typ. 160µA (normal communication)
Current consumption LEDs (alarm condition)	typ. 6mA
Ambient temperature	-30°C to +70°C (no icing)
Relative humidity	5 – 95% (no condensation)
Dimensions Ø × H (without base)	106 × 50 (mm)
Colour	white
Weight	86g
Approvals	VdS G213043 LPCB 928b/02 2831-CPR-F4314
Order number	241086
Order name	Optical Smoke Detector/750 FI750/O

