



Datasheet

Please read this user manual carefully before operation.

Performance Feature

- Three MIC input , two AUX input, one AUX output, suit for PA system.
- 70V,100V line voltage output and 4 Ohm~ 16Ohm constant resistance (balance)output
- MIC 1 has priority input and mute function
- Individual volume control for MIC and AUX
- Bass and treble control
- MP/USB/SD/FM/Bluetooth input
- Five LED indicators of level meter, convenient to monitor the working state
- Output short circuit protection and alarm
- 5 channel port output
- This amplifier can be a small PA system

Parameter

Model	CE-MP70SE	CE-MP130SE	CE-MP260SE	CE-MP360SE	CE-MP460SE	CE-MP660SE
Rated Power	70W	130W	260W	360W	460W	660W
Power Consumption	0.25KVA	0.3KVA	0.7KVA	<0.7KVA	<0.7KVA	<0.7KVA
Net Weight.	9.8KG	11KG	12.1KG	14.1KG	16KG	18KG
Gross Weight	11.3KG	12.5KG	13.6KG	15.6KG	17.5KG	19.3KG
Fuse Size	F4AL250V	F6AL250V	F8AL250V	F8AL250V	F8AL250V	F8AL250V
Dimension	89mm × 483mm × 366mm					
Power	AC200~240V, 50/60Hz					
Microphone Input Sensitivity	8-11MV					
Line Input	280MV-320MV					
Line Output	1V ± 10%					
Frequency Response	60Hz-15KHz(± 3dB)					
Signal Noise Ratio(SNR)	> 70dB					
Total Harmonic Distortion (THD)	≤ 2% (80Hz-12.5KHz)					
	≤ 2% (Under Rated Condition, 80Hz-12.5KHz)					
	≤ 4%(1/100 Rated Power Output,80Hz-12KHz)					
Output Mode	70V/100V Output; 4~16Ω Output					
Mute Function	When MIC1 has signed input, other signal attenuate :0~-35dB					
Tone Adjust Range	Bass: ±10dB(100Hz) Treble: ±10dB(10KHz)					