
Push Button Series



		SOYAL
38-PB ted IR Push Button : 3-5cm)		-PB-6A/7A/8A jezo Push Button
(LED ON:Green&Red)	(LED OFF) (LE	Bi-color LED ED ON:Green&Red) (LED ON:Blue&Red)
in and aesthetics, Bi-color LED ring shine and trigger door lock without touching, suited in ndards. oice and installation on various sites. le according to user needs. Iterference design table for indoor and outdoor installation. is adjustable according to the needs.	 Flush mounted design is thin and aesthetics, Bi-color LED ring shine and light your life. Three types for installation on various sites: Slim type, US type and EU type. Ultra-thin design for direct installation & cutting hole. Waterproof rating IP65, suited to indoor and outdoor use; registered patent certification for waterproof LED Piezo push button and SGS waterproof certification. Power switch contact with current protection design. Bi-color LED design help you quickly find out push button in low lighting environment. 	
ndby: 35mA / Max. during activation: 65mA / 125VAC 0.3A	Voltage Current Contact capacity	None / DC 12V(LED) LED :12VDC / 10mA DC5~24V / 100mA
n C)	Output Contact	N.O. 7mm 1
→ 9 ← +-33 → 122		114.3(H)X44.5(W)X7(D) N/A / EXIT
88US X9/42(D) YAL	AR-PB-7A 114.3(H)X70(W)X7(D) N/A / EXIT	
	(NCC <u>WWW</u>	AR-PB-8A 86(H)X86(W)X7(D) N/A / EXIT Soyal.com V200515